

Model Information



■ Main Features

- USB 2.0 to 2 x RS232/422/485
- High-Speed serial ports 921.6kbps
- Driver for Windows, Linux, Mac OS X
- LEDs for Power and TxD/RxD activity
- ESD protection on USB and serial ports
- 2.5kV electrical isolation (ISO version only)
- Metal housing and Bus powered
- DIN-Rail and wall mount options
- Wide range of operating temperatures

[Contact Online...](#)

USB-2COM Plus USB-2COM Plus ISO

(USB-2COM-PRO, USB-2COM-M, USB-2COMi-M, USB-2COMi SI-M)

Quick Link: | [Main Features](#) | [More Pictures](#) | [Overview](#) | [USB Interface](#) | [Serial Interface](#) | [Software](#) | [Power Requirement](#) | [Housing and Mounting](#) | [Environmental Data](#) | [Standards and Certifications](#) | [MTBF \(Mean Time Between Failures\)](#) | [Warranty](#) | [Ordering Information](#) | [Options](#) | [Packaging](#) |

■ More Pictures



Click on the thumbnails for the large picture ...

[>Back to top](#)

■ Overview

The USB-2COM Plus provides easy serial port expansion over USB 2.0 connecting to high speed RS232 or RS422/485 devices. The device is fully ESD and surge protected, bus powered and accommodated in a metal case. Furthermore, it can operate across a large range of temperature levels to cope with harsh operating conditions. The ISO version is 2.5kV electrically isolated to withstand unbalanced ground loops that arise in hazardous industrial environment. Lastly, both DIN-Rail and wall-mounting options are available.

Flexible Three-Way Serial Ports

The serial ports allow different operating modes — which are easily configured using the rear DIP switch — to fully support RS232, RS422 and RS485 protocols. The differential line termination for RS485 (120Ω) is automatically controlled by choosing the appropriate operating mode. High/Low biasing resistors are not needed; as such, hassle-free usage is guaranteed for the user. Com Port drivers are available for Windows, Linux and Mac OS X. A configuration tool allows easy access to special Windows driver options.

High Speed and Isolation

USB 2.0 Full Speed connection allows serial data rates of up to 3Mbps for RS422/485 and 921.6kbps for RS232. Every non-standard bitrate (e.g. 500kbps) can easily be set up in the range of up to 960 kbps.

USB-xCOM Plus adapters are 16kV ESD and surge protected at USB and serial ports interfaces. Additionally, the serial ports are 2.5kV electrically isolated (ISO version only), making them ideal for deployment in harsh industrial environments.

Port Expansion for NetCom Plus 1P and 2P

USB-COM Plus 1 and 2 port adapters can be used to expand the serial ports for NetCom Plus Servers (1 and 2 ports).

Small & Powerfull System, No rotation items, for hard industrial envions, for automation, robot- and cashsystems

■ USB Interface

USB-Input	USB 2.0 Full Speed, USB 1.1 compliant
Connector	USB type B
Circuits	FTDI FT2232D

[>Back to top](#)

■ Serial Interface

No. of Ports/Type	2 x RS232/422/485 configured by DIP switch
Connector	DB-9 male
Protection	<ul style="list-style-type: none"> • 16kV ESD surge protection • 2.5kV Electrical isolation on ISO version
Operating Modes	<ul style="list-style-type: none"> • RS232 • RS422 full duplex (120Ω on/off) • RS485 4 wire, full duplex (120Ω on/off) • RS485 2 wire, half duplex (120Ω on/off)
Configuration	One DIP switch sets the operating mode and RS422/485 termination No High/Low biasing resistors needed
Signals non-ISO	<ul style="list-style-type: none"> • RS232: TxD, RxD, RTS, CTS, DTR, DSR, DCD, RI, GND • RS422: Tx+/-, Rx+/-, GND • RS485 4-wire: Tx+/-, Rx+/-, GND • RS485 2-wire: Data+/-, GND
Signals ISO	<ul style="list-style-type: none"> • RS232: TxD, RxD, RTS, CTS, GND • RS422: Tx+/-, Rx+/-, GND • RS485 4-wire: Tx+/-, Rx+/-, GND • RS485 2-wire: Data+/-, GND <p>All signals isolated for 2.5kV</p>
RS485 Data Direction Control	ARTc (Automatic Receive Transmit control)
Data Bits	7, 8
Stop Bits	1, 2
Parity	None, Even, Odd, Mark, Space
Flow Control	RTS/CTS, XON/XOFF
Baudrate	<ul style="list-style-type: none"> • RS232: 180bps - 921.6/1000kbps • RS422: up to 3Mbps • RS485: up to 3Mbps
LEDs	TxD/RxD for each port

[>Back to top](#)

■ Software

Drivers	<ul style="list-style-type: none"> • Windows 2000 to Windows 10 (x86 and x64) • Windows Server 2000 to 2016 (x86 and x64) • Linux (Kernel 3.4 and later built-in) • Mac OS X
Installation	The driver is already installed (Linux), or installs by automatic Download after Device connection (Windows).

[>Back to top](#)

■ Power Requirement

Input Voltage	5V (USB)
Power Consumption	210mA 1W
Connector	USB Type B, bus powered, no external supply

[>Back to top](#)

■ Housing and Mounting

Case	0.8mm sheet metal
-------------	-------------------

Weight	0.25kg, w/h box 0.3kg
Dimensions	115×73×25 mm ³ (W×L×H)
Packaged	150×107×48 mm ³
Mounting	<ul style="list-style-type: none"> • DIN-Rail (optional) • Wall mount (optional)

[>Back to top](#)

■ Environmental Data

Operating Temp	–25°C - 75°C
Storage Temp	–30°C – 85°C
Ambient Humidity	5-95% non condensing

[>Back to top](#)

■ Standards and Certifications

Declarations	CE, FCC
EMI	<ul style="list-style-type: none"> • EN 55022 Class B • 47 CFR FCC Part 15 Subpart B
EMS (EN 55024)	<ul style="list-style-type: none"> • EN 61000-4-3: Radiated RFI • EN 61000-4-4: Electrical Fast Transient • EN 61000-4-5: Surge • EN 61000-4-6: Induced RFI • EN 61000-4-8: Power Frequency Magnetic Field • EN 61000-4-11: Power supply dips
ESD	EN 61000-4-2 4kV contact 8kV air for <ul style="list-style-type: none"> • Serial Port • USB

[>Back to top](#)

■ MTBF (Mean Time Between Failures)

MTBF non-ISO	139.2 Years @ 25°C 73.7 Years @ 45°C
MTBF ISO	79.2 Years @ 25°C 34.2 Years @ 45°C
Standard	Telcordia (Bellcore) Standard; RelCalc. 5.0 BELL-7

[>Back to top](#)

■ Warranty

Warranty Period	2 years
------------------------	---------

[>Back to top](#)

■ Ordering Information

605	USB-2COM Plus (2x RS232/422/485, non-isolated)
607	USB-2COM Plus ISO (2x RS232/422/485, isolated)

[>Back to top](#)

■ Options

6692	DK-NCP DIN-Rail mounting kit (clamp on rear side)
6693	WK-NCP Wallmount kit
663	DB9F-to-TB/5Pins for free wiring option
6061	DB9F-to-RJ45 for changing from DB9 to CAT5 wiring (Optimised for RS422/485 operating modes)
6062	RJ45-to-DB9M for changing back from CAT5 to DB9 wiring (Required to match the DB9 pinout at USB-xCOM Plus)
661	Serial Null-Modem adapter 9PF-9PF, change male to female

[>Back to top](#)

■ Packaging

Packing list

- USB-2COM Plus device
- USB 2.0 High-Speed cable
- 4 rubber feet for table mode

[>Back to top](#)

- * Specifications are subject to change without notice.
- * All trademarks and brands are property of their rightful owners.

USB-2COM Plus USB-2COM Plus ISO

[>Back](#)



USB-COM Plus Configurator

[>Back](#)

VScom USB-COM Plus Configurator
— □ ×

File Help

Present COM-Ports Show disconnected devices

COM3

COM4

COM6

Port Settings

Min. Read Timeout (ms):

Min. Write Timeout (ms):

Polling Period:

Latency Timer:

Default Settings

Optimize for USB-COM

Baud Rate Mappings

Buffered Writes

Rename COM Port

Refresh

Serial Enumerator

Serial Printer

Cancel If Power Off

Event On Surprise Removal

Set RTS On Close

Disable Modem Ctrl At Startup

Optimize for USB-CAN

Global Settings

Ignore Hardware Serial Number

Reload Driver

Cancel

Close All Ports
VScom USB-COM 232, SN: DN6NP3AA, ID: 4036015, LocalID: 31; Open COM Ports: 0

Terminal Block Adapter

[>Back](#)



DIN-Rail Mount Kit DK-NCP

[>Back](#)



Wall Mount Kit

[>Back](#)



DK-NCP: USB-COM Plus on DIN-Rail

[>Back](#)



DSK-NCP: Side-mount on DIN-Rail
[>Back](#)



(2021 Mar 19)