

## Model Information



### ■ Main Features

- USB 2.0 to 1 x RS232/422/485
- High-Speed serial ports 921.6kbps
- Driver for Windows, Linux, Mac OS X
- LEDs for Power and TxD/RxD activity
- ESD protection on USB and serial ports
- 2.5kV electrical isolation (ISO version only)
- Small metal housing and Bus powered
- DIN-Rail and wall mountable
- Wide range of operating temperatures

[Contact Online...](#)

## USB-COM Plus Mini ISO (USB-COMi-M, USB-COMi SI-M)

Quick Link: | [Main Features](#) | [More Pictures](#) | [Overview](#) | [USB Interface](#) | [Serial Interface](#) | [Software](#) | [Power Requirement](#) | [Housing and Mounting](#) | [Environmental Data](#) | [Standards and Certifications](#) | [MTBF \(Mean Time Between Failures\)](#) | [Warranty](#) | [Ordering Information](#) | [Options](#) | [Packaging](#) |

### ■ More Pictures



Click on the thumbnails for the large picture ...

[>Back to top](#)

### ■ Overview

USB-COM Plus Mini provides easy serial port expansion over USB 2.0 connecting to high speed RS232 or RS422/485 devices. The device is fully ESD and surge protected, bus powered and accommodated in a tiny metal case. Furthermore, it can operate across a large range of temperature levels to cope with harsh operating conditions. The ISO version is 2.5kV electrically isolated to withstand unbalanced ground loops that arise in hazardous industrial environment. Lastly, both DIN-Rail and wall-mounting options are available.

#### Flexible Three-Way Serial Ports

The serial port allows different operating modes — which are easily configured using the bottom DIP switch — to fully support RS232, RS422 and RS485 protocols. The differential line termination for RS485 (120Ω) is automatically controlled by choosing the appropriate operating mode. High/Low biasing resistors are not needed; as such, hassle-free usage is guaranteed for the user.

Com Port drivers are available for Windows, Linux and Mac OS X. A configuration tool allows easy access to special Windows driver options.

#### High Speed and Isolation

USB 2.0 full speed connection allows serial data rates of up to 3Mbps for RS422/485 and 921.6kbps for RS232. Every non-standard bitrate (e.g. 500kbps) can easily be set up in the range of up to 960 kbps.

The USB-COM Plus Mini is fully ESD and surge protected at the USB and serial port interfaces. Additionally, the serial port are 2.5kV electrically isolated (ISO-version only), making it ideal for deployment in hazardous industrial environments.

### ■ USB Interface

<b>USB-Input</b>	USB 2.0 Full Speed, USB 1.1 compliant
<b>Connector</b>	USB type B
<b>Circuits</b>	FTDI FT231XS
<a href="#">&gt;Back to top</a>	
<b>■ Serial Interface</b>	
<b>No. of Ports/Type</b>	1 x RS232/422/485 configured by DIP switch
<b>Connector</b>	DB-9 male
<b>Protection</b>	<ul style="list-style-type: none"> <li>• 16kV ESD surge protection</li> <li>• 2.5kV Electrical isolation on ISO version</li> </ul>
<b>Operating Modes</b>	<ul style="list-style-type: none"> <li>• RS232</li> <li>• RS422 full duplex (120Ω on/off)</li> <li>• RS485 4 wire, full duplex (120Ω on/off)</li> <li>• RS485 2 wire, half duplex (120Ω on/off)</li> </ul>
<b>Configuration</b>	One DIP switch sets the operating mode and RS422/485 termination No High/Low biasing resistors needed
<b>Signals non-ISO</b>	<ul style="list-style-type: none"> <li>• RS232: TxD, RxD, RTS, CTS, DTR, DSR, DCD, RI, GND</li> <li>• RS422: Tx+/-, Rx+/-, GND</li> <li>• RS485 4-wire: Tx+/-, Rx+/-, GND</li> <li>• RS485 2-wire: Data+/-, GND</li> </ul>
<b>Signals ISO</b>	<ul style="list-style-type: none"> <li>• RS232: TxD, RxD, RTS, CTS, GND</li> <li>• RS422: Tx+/-, Rx+/-, GND</li> <li>• RS485 4-wire: Tx+/-, Rx+/-, GND</li> <li>• RS485 2-wire: Data+/-, GND</li> </ul> <p>All signals isolated for 2.5kV</p>
<b>RS485 Data Direction Control</b>	ARTc (Automatic Receive Transmit control)
<b>Data Bits</b>	7, 8
<b>Stop Bits</b>	1, 2
<b>Parity</b>	None, Even, Odd, Mark, Space
<b>Flow Control</b>	RTS/CTS, XON/XOFF
<b>Baudrate</b>	<ul style="list-style-type: none"> <li>• RS232: 180bps - 921.6/1000kbps</li> <li>• RS422: up to 3Mbps</li> <li>• RS485: up to 3Mbps</li> </ul>
<b>LEDs</b>	bicolour TxD/RxD for each port
<a href="#">&gt;Back to top</a>	
<b>■ Software</b>	
<b>Drivers</b>	<ul style="list-style-type: none"> <li>• Windows 2000 to Windows 10 (x86 and x64)</li> <li>• Windows Server 2000 to 2016 (x86 and x64)</li> <li>• Linux (Kernel 3.4 and later built-in)</li> <li>• Mac OS X</li> </ul>
<b>Installation</b>	The driver is already installed (Linux), or installs by automatic Download after Device connection (Windows).
<a href="#">&gt;Back to top</a>	
<b>■ Power Requirement</b>	
<b>Input Voltage</b>	5V (USB)
<b>Power Consumption</b>	max 85mA, 420mW
<b>Connector</b>	USB Type B, bus powered, no external supply
<a href="#">&gt;Back to top</a>	
<b>■ Housing and Mounting</b>	
<b>Case</b>	0.8mm sheet metal
<b>Weight</b>	150g, w/h box 0.3kg
<b>Dimensions</b>	50×72×22 mm <sup>3</sup> (W×L×H) Case 72×72×22 mm <sup>3</sup> (W×L×H) with mounting wings

<b>Packaged</b>	85×122×55 mm <sup>3</sup>
<b>Mounting</b>	<ul style="list-style-type: none"> <li>• DIN-Rail (optional)</li> <li>• Wall mount</li> </ul>
<a href="#">&gt;Back to top</a>	
<b>■ Environmental Data</b>	
<b>Operating Temp</b>	–25°C - 75°C
<b>Storage Temp</b>	–30°C – 85°C
<b>Ambient Humidity</b>	5-95% non condensing
<a href="#">&gt;Back to top</a>	
<b>■ Standards and Certifications</b>	
<b>Declarations</b>	CE, FCC
<b>EMI</b>	<ul style="list-style-type: none"> <li>• EN 55022 Class B</li> <li>• 47 CFR FCC Part 15 Subpart B</li> </ul>
<b>EMS (EN 55024)</b>	<ul style="list-style-type: none"> <li>• EN 61000-4-3: Radiated RFI</li> <li>• EN 61000-4-4: Electrical Fast Transient</li> <li>• EN 61000-4-5: Surge</li> <li>• EN 61000-4-6: Induced RFI</li> <li>• EN 61000-4-8: Power Frequency Magnetic Field</li> <li>• EN 61000-4-11: Power supply dips</li> </ul>
<b>ESD</b>	EN 61000-4-2 4kV contact 8kV air for <ul style="list-style-type: none"> <li>• Serial Port</li> <li>• USB</li> </ul>
<a href="#">&gt;Back to top</a>	
<b>■ MTBF (Mean Time Between Failures)</b>	
<b>MTBF</b>	available soon
<b>Standard</b>	Telcordia (Bellcore) Standard; RelCalc. 5.0 BELL-7
<a href="#">&gt;Back to top</a>	
<b>■ Warranty</b>	
<b>Warranty Period</b>	2 years
<a href="#">&gt;Back to top</a>	
<b>■ Ordering Information</b>	
<b>655</b>	USB-COM Plus Mini (1x RS232/422/485, non-isolated)
<b><a href="#">656</a></b>	USB-COM Plus Mini ISO (1x RS232/422/485, isolated)
<a href="#">&gt;Back to top</a>	
<b>■ Options</b>	
<b><a href="#">662</a></b>	DK 35A DIN-Rail mounting kit
<b><a href="#">663</a></b>	DB9F-to-TB/5Pins for free wiring option
<b><a href="#">6061</a></b>	DB9F-to-RJ45 for changing from DB9 to CAT5 wiring (Optimised for RS422/485 operating modes)
<b><a href="#">6062</a></b>	RJ45-to-DB9M for changing back from CAT5 to DB9 wiring (Required to match the DB9 pinout at USB-COM Plus Mini)
<b><a href="#">661</a></b>	Serial Null-Modem adapter 9PF-9PF, change male to female
<a href="#">&gt;Back to top</a>	
<b>■ Packaging</b>	
<b>Packing list</b>	<ul style="list-style-type: none"> <li>• USB-COM Plus Mini device</li> <li>• USB 2.0 High-Speed cable</li> <li>• 4 rubber feet for table mode</li> </ul>
<a href="#">&gt;Back to top</a>	

\* Specifications are subject to change without notice.

\* All trademarks and brands are property of their rightful owners.

**USB-COM Plus Mini ISO**  
[>Back](#)



## USB-COM Plus Configurator

[>Back](#)

VScom USB-COM Plus Configurator

File Help

Present COM-Ports  Show disconnected devices

COM3  
COM4  
COM6

Port Settings

Min. Read Timeout (ms):  Serial Enumerator

Min. Write Timeout (ms):  Serial Printer

Polling Period:  Cancel If Power Off

Latency Timer:  Event On Surprise Removal

Set RTS On Close

Disable Modem Ctrl At Startup

Default Settings

Optimize for USB-COM

Optimize for USB-CAN

Baud Rate Mappings

Buffered Writes

Rename COM Port

Global Settings

Ignore Hardware Serial Number

Reload Driver

Refresh OK Cancel Apply

Close All Ports

VScom USB-COM 232, SN: DN6NP3AA, ID: 4036015, LocalID: 31; Open COM Ports: 0

## Terminal Block Adapter

[>Back](#)



(2021 Mar 19)